# Lever-type Detector Switches SW1AB-500-T11

1/9

### Features


- Miniaturized for space saving design.
- ⇒Superior reliability at micro-current by employing a sliding contact.
- This is a compact detector switch which can be pressed either horizontally or vertically.
- Reflow soldering is possible.

# Applications



Zoom

# ■ Products Number System



Mechatronic detection for audio and VCR Digital cameras.



Actual size

## Products Line

| No | Products No   | Pole | Position | Quantity<br>(pcs./reel) | Notes |
|----|---------------|------|----------|-------------------------|-------|
| 1  | SW1AB-500-T11 | 1    | 1        | 1,100                   |       |

Typical Specifications

| Typical Specifications   |  |  |  |  |
|--------------------------|--|--|--|--|
| Item                     | Specification                            |  |  |  |
| Ratings (max.)           | 0.05 to 10mA 3 to 5V DC (Resistive load) |  |  |  |
| Contact resistance       | 1 ohm max.                               |  |  |  |
| Insulation resistance    | 100 megohm min. 100V DC                  |  |  |  |
| Withstanding voltage     | 100V AC for 1min.                        |  |  |  |
| Operating life with load | 50,000 cycles                            |  |  |  |
| Operating force          | 0.25N max.                               |  |  |  |

Dimensions

No Style

SW1AB-500-T11

#### Notes

- 1. The appearance and specifications of the product may be modified to improve its performance without prior notice.
- 2. This catalog shows only outline specifications. When using the product, please obtain formal specifications.
- 3. Please see appendix [Cautions in Using Switches].
- 4. This switch is not washable.
- 5. Soldering shall be done with actuator at free position and take care not to attach flux on plastic portion.
- 6. Note that if the stress is applied to the terminals during soldering, they might cause deformation and defects in electrical performance.
- 7. In manual soldering, consideration should be given to apply the soldering iron to the tip of the terminal so that unusual pressure is not applied to the terminal.
- 8. In case circuit and software design consideration against chattering and bouncing shall be taken as below.

Read a few times. (Ex. 5ms for 5 times)

Set delay time.

Set integral circuit.

- 9. As to threshold voltage, center setting is recommended.
- 10. Care shall be taken not to apply stress to the body of switch as it may affect the performance.
- 11. Please confirm the performance on actual operation by simulation with actual environment environments for high reliability.